

UDM_{HV}



EtherCAT® Single & Dual Axis 480Vac Drive Module

- Universal single and dual axis EtherCAT Drive Modules
- 230 - 480Vac with up to 15/30A continuous / peak current
- 230Vac with up to 20/60A continuous / peak current
- Exceptional Servo Performance
- Two feedback inputs per axis
- Supports incremental digital & analog encoders, absolute encoders & resolver
- Digital I/O: 8 inputs, 8 outputs
- Analog I/O: 4 inputs, 2 outputs, 12 bit resolution
- Safe Torque Off (STO)

The UDM_{HV} is a line of EtherCAT universal single & dual axis economical drives for AC servo / DC Brushless, AC Induction*, and DC brush motors. The UDM_{HV} operates as an EtherCAT node under any SPiiPlus EtherCAT master Controller including the PC based SPiiPlusSC Soft Controller. It is designed to address cost sensitive applications requiring high dynamics and large loads.

The UDM_{HV} is offered with the following current levels (cont./peak): 5A/10A, 10A/20A, 15A/30A, 20A/20A + 5A/10A with 230-480Vac, and 10A/30A, 15A/45A, 20A/60A with 230Vac.

The module is powered by 3 phase 230 to 480Vac. In addition to the AC supply, the UDM_{HV} is supplied by a separate 24Vdc control supply that keeps all low voltage signals alive during emergency conditions.

When a 230Vac - 480Vac module is operated below 400Vac, the output cont./peak current levels increase by 25%.

Optional Safe Torque Off (STO) module cuts the power to the motor without removal of the power source to comply with SIL-3 and PLe safety levels.

CE (Pending), **UL**

EtherCAT® is registered trademark and patented technology, licensed by Beckhoff Automation GmbH, Germany

Contact us: sales@acsmotioncontrol.com | www.acsmotioncontrol.com

**In-Position
Technologies**
www.iptech1.com

ACS
MOTION CONTROL

Specifications

Product X - number of Axes YY - Other configuration options	UDM _{HV} X-A-YY	UDM _{HV} X-B-YY	UDM _{HV} X-C-YY	UDM _{HV} X-D-YY	UDM _{HV} X-E-YY	UDM _{HV} X-F-YY	UDM _{HV} X-G-YY	UDM _{HV} X-H-YY
Number of axes	1 or 2							
Control voltage input [Vdc]	24 +/- 10%							
Motor voltage input range [Vac]	3 phase, 230 – 480				3 phase, 230			
PWM frequency [KHz]	10				20			
Phase Current per axis Cont./Peak sine amplitude at Vmax 480V [A]	5/10	10/20	15/30	20/20 + 5/10	-	-	-	-
Phase Current per axis Cont./Peak sine amplitude at Vmax 400V [A]	6.25/12.5	12.5/25	18.75/37.5	25/25 + 6.25/12.5	-	-	-	-
Phase Current per axis Cont./Peak sine amplitude at Vmax 230V [A]	6.25/12.5	12.5/25	18.75/37.5	25/25 + 6.25/12.5	5/15	10/30	15/45	20/60
Peak current time [sec]	1							
Max. output voltage to motor phase-to-phase [Vrms]	(Vac in) x 95%				(Vac in) x 88%			
Max. input continuous power @ 480 Vac [kVA]	7.6	15.1	22.7*	19	-	-	-	-
Max. input continuous power @ 400 Vac [kVA]	7.7	15.4	19.3*	19.3*	-	-	-	-
Max. input continuous power @ 230 Vac [kVA]	4.3	8.8	11.1*	10.9*	3.5	6.7	10.2	13.4
Min. load Inductance, at maximum motor voltage [mH]	1							
Max. output power (cont./peak) per axis @ 480 Vac [KW]	2.6/4.9	5.1/9.9	7.7/14.8	10.4+2.6/ 10.3+5.1	-	-	-	-
Max. output power (cont./peak) per axis @ 400 Vac [KW]	2.6/5	5.2/10	7.9/15.2	10.6+2.6/ 10.4+5.2	-	-	-	-
Max. output power (cont./peak) per axis @ 230 Vac [KW]	1.5/2.8	2.9/5.7	4.4/8.5	5.8+1.5/ 5.8+2.9	1.2/3.3	2.2/6.3	3.5/9.7	4.5/12.7
Max. Heat dissipation per axis @ 480 Vac [W]	50	102	156	211+50	-	-	-	-
Max. Heat dissipation per axis @ 400 Vac [W]	54	111	172	235+54	-	-	-	-
Max. Heat dissipation per axis @ 230 Vac [W]	36	75	117	162+36	48	98	84	114
Weight [Kg]	5.3							
Dimensions [mm ³]	260 x 246 x 120							
Standards	CE, UL (Pending)							

* Phase input current is limited to 27.8Arms

Servo

A standard comprehensive set of powerful algorithms to enhance accuracy, move & settle time, smooth velocity, stability and robustness

- Advanced PIV cascaded structure
- Loop shaping filters
- Gain Scheduling
- Gantry MIMO control
- Dual feedback / loop control
- Disturbance rejection control

Drives

Type: digital current control with field oriented control and space vector modulation

Current ripple frequency: 20 kHz for A, B, C, D drivers and 40KHz for E, F, G, H drivers
Current loop sampling rate: 20 kHz
Programmable current loop bandwidth: up to 4kHz, will vary with tuning & load parameters.

Commutation type: sinusoidal. Initiation with and without hall sensors
Switching method: advanced unipolar PWM

Protection: Short current (phase-to-phase or phase to ground), Over current, Over temperature

Supplies

The module is fed by two power sources. A drive AC supply and a 24Vdc control supply
During emergency conditions there is no need to remove the 24Vdc control supply

Drive Supply

Range: 230 to 480Vac, or 230Vac, see 'ordering options' for the different configurations.

Current rating should be calculated based on actual load

Control Supply

Range: 24Vdc ± 10% Maximum input current / power: 4A / 100W
Note: The module consumes 2A (50W) Additional 2A are needed when the motor brake feature is used.

Regeneration

Internal and external options

Internal: 150Ω/300W for 230 - 480Vac modules

50Ω/300W for 230Vac modules

External: 50Ω/300W for 230Vac, 150Ω/300W for 480Vac

(see ordering options field 16)

Motor Types

Two- and three-phase permanent magnet synchronous (DC brushless/AC servo), DC brush, Voice coil, Two- and three-phase stepper (micro-stepping open or closed loop), AC induction*.

* Consult ACS.

Feedback

Up to 4 feedback devices. The following are supported:

Incremental Digital Encoder

Up to four, two per axis, AqB,I; Clk/Dir,I
RS-422. Max. rate: 50 million encoder counts/ sec.
Protection: Encoder error, not connected

Sin-Cos Analog Encoder (optional)

Up to two, one per axis.1Vptp, differential
Multiplication factor: From x4, to- x4,096, frequency: 250kHz.
Automatic compensation of Offset, Phase and Amplitude. Squared Sin-Cos output option
Maximum acceleration: 10⁸ million sine periods/sec².
Protection: Encoder error, not connected

Absolute Encoder (optional)

Up to two, EnDat 2.1(Digital)/2.2, Smart-Abs, Panasonic, Hiperface, Biss-C, SSI

Resolver

Two, 12b resolution (4,096 counts/rev)

Hall inputs for initial commutation

One set of three per axis, Single-ended, 5V, source, opto-isolated.
Input current: <7mA

Digital I/O

General Purpose Inputs

Eight, Single-ended, 24V±20%, opto-isolated, source.
(optional 5V & sink configuration upon order) Input current: 4-14mA

Safety Inputs

Left + right limit per axis, Single-ended, 24V±20%, opto-isolated, source.
optional 5V & sink configuration upon order, Input current: 4-14mA.
E-Stop: Opto-isolated, floating two-terminal

MARK (High Speed Position Capture)

Four. Two are RS422 with dedicated inputs and can be used as GP inputs.
Two share General Purpose Inputs 6,7

General Purpose Outputs

Eight, Single-ended, 24V±20%, opto-isolated, source. 0.5A per output with
up to 3A for all outputs

Motor Brake outputs

One per axis, 24V, 1A, opto-isolated.
Powered by the 24V Control Supply

PEG (Position Event Generator)

Two PEG Pulse and two PEG State, RS422.
Flexible axis assignment. Can be used as GP outputs.
Two general purpose opto-isolated outputs can be programmed to
be used as the PEG Pulse outputs. Pulse width with RS422 outputs:
26nSec to 1.75mSec.
Maximum rate with RS422 outputs: 10MHz
Pulse width with GP outputs: 0.75mSec to 1.75mSec.
Maximum rate with GP outputs: 1kHz

HSSI

One channel, RS422, Flexible assignment to both axes

STO

Two pairs of inputs

Analog I/O

Analog Inputs

Four, ±10V, differential, 12 bit resolution. 20kHz sampling rate. Can be used
as feedback to the servo loops

Analog Outputs

Two, ±10V, differential, 10 bit resolution. Sampled at the servo sampling rate

Host Communication Ports

Serial: One, Modbus protocol as slave
EtherCAT ports: Two, In & Out, 100 Mbit/sec, CoE and FoE protocols

Environment

Operating range: 0 to + 40°C
Storage and transportation range: -25 to +60°C
Humidity (operating range): 5% to 90% non-condensing

Accessories

Mating Connectors Kit: PN CMhvUDMhv-ACC1
J11 mating connector +2m cable, flying leads: PN CMhvUDMhv-ACC2
Clamping Yoke: PN CMhvUDMhv-ACC3
Cover fan kit: PN HV COVER FAN ACC1
Heatsink fan kit: PN HV HEATSINK FAN ACC1
STO kit, 2 meter cable with flying leads for STO: PN STO-ACC1
STO kit, Connector Kit for STO card: PN STO-ACC2

Example: UDM_{hv}2A12B1YSAN

Field	1	2	3	4	5	6	7	8	9	10
UDM _{hv}	2	A	1	2	B	1	Y	S	A	N

Ordering Options

	Field	Example selection by user	Optional Values
Number of built-in drives	1	2	1, 2
Voltage & current rating of built-in drives (cont/peak)	2	A	(A): 230-480V, 5/10A, (B): 230-480V, 10/20A, (C): 230-480V,15/30A, (D): 230-480V, 20/20A+5/10A, (E): 230V, 5/15A, (F): 230V, 10/30A, (G): 230V, 15/45A, (H): 230V, 20/60A
250kHz Sin-Cos encoder interface	3	1	0, 1, 2
Total number of feedback channels	4	2	2, 4
Absolute encoders type	5	B	None (N), EnDAT 2.1(digital)/2.2 (E), Smart Abs (S), Panasonic (P), Hiperface (H), Resolver (R), BiSS-A/B/C (B), SSI (I)
Number of Absolute encoder channels	6	1	0, 1, 2
STO	7	Y	Yes (Y), No (N)
I/O configuration	8	S	(N): Inputs & limits: 24V/SOURCE (PNP), outputs: 24V/SOURCE (PNP). (D): Identical to (N). For compatibility reasons. (S): Inputs & limits: 24V/SINK (NPN), Outputs: 24V/SOURCE (PNP). (U): Inputs: 24V/SOURCE (PNP), Limits 24V/SINK (NPN), Outputs: 24V/SOURCE (PNP).
Built-in Shunt Resistor	9	A	None (N), 50Ω/300W for 230Vac (A), 150Ω/300W for 480Vac (B)
NanoPWM	10	N	No (N)